

11. Code Setting

To set the coding for the Dogtra EDGE transmitter to an existing receiver/collar, or an Additional receiver/collar, follow the steps below.



1. Start by turning on the transmitter by holding down the on/off button on the back of the transmitter.



2. Set the transmitter's intensity dial to "0", and the mode selection dial to "C".



3. In the off position hold down the receiver/collar on/off button until the green LED indicator light begins to blink rapidly.



4. Immediately press the button on the transmitter of the color you would like the receiver/collar to be coded to.

***Attention:** Turn the mode selection dial to "P", or "L", to check that unit has been coded properly.